

## **TECHNICAL DATA SHEET**



## Single loop analogue addressable fire control panel

The HS-5100 control panels are supplied with a single loop driver card, 2 on-board sounder circuits, 20 programmable zonal LED's and 4 programmable function buttons.

The control panel consists of the latest dual flash-based microprocessor technology combined with a high resolution graphical LCD display and tactile keypad for engineering configuration and end-user operation.

Powerful cause and effect programming coupled with 'DynamiX' zoning makes the panel suitable for a wide range of applications from small to large complex multi-area systems.

An extensive suite of user-friendly Windows based PC software is available for configuration, service management and logo programming.

Simply adding a network card allows the panel to communicate with any other Elan or network peripheral including; remote display units, 'ipGateway' or BMS/ Graphical Interface.



## **Features**

## **Main Features**

- Single loop analogue fire control panel
- 20 programmable zonal / 25 system LED's with slide in labels
- Dedicated loop driver for Apollo & Hochiki protocol support
- Graphical LCD user interface and support for up to 200 fire zones allowing full EN54 compliance without additional hardware expansion
- Dual flash-based microprocessor technology with real-time clock on-board
- Dedicated USB & RS232 Serial Port for direct PC or modem connection
- Installer friendly 'Auto-Learn',
  'Loop Detection' and on-board scope facility for ease of commissioning and fault finding
- Fully programmable via the on-board keypad or PC configuration tools

- The graphical display can be configured to operate with virtually any language or character set and allow the installer's logo to be applied using the 'Logo' application software
- Robust removable equipment chassis with plug-in connectors for simple fixing and cable termination
- Integral 'P-Bus' for system expansion via available option cards
- Connection to the 'Ad-Net' peer-to-peer network is achieved using a simple plug-in network card allowing the system to share up to 2000 zones with full cross panel reporting, control and site-wide cause and effect functionality

Technical specifications				
Base Technology	Dual flash-based processors with real-time clock, trace diagnostics, programmable languages and character sets			
Display	Backlit 240 x 64 graphical LCD			
LED Indicators	22 red (1 x Fire, 1 x More Alarms, 20 x Zonal Programmable), 1 green (Power), 13 amber and 12 bi-colour (Fault & System)			
Controls	Alpha numeric keypad permitting navigation, Reset, Mute, Silence, Resound, Evacuate and 4 x programmable push buttons			
Protocol	Apollo (XP95/Discovery), Hochiki ESP			
Number of Fire Zones	2000 'DynamiX' (200 per individual panel)			
Number of Loops				
Devices per Loop	Protocol dependant			
Loop Current	500mA			
On-Board Sounder Circuits	2 x 1 amp, programmable			
On-Board Relays	2 x 1 amp, 30v AC/DC programmable (10mA, 5v min) - Expandable using HS-507			
Auxiliary Supply	1 x 24v, 500mA			
Programmable Input	1 x monitored, programmable input, on-board			
Programmable key switch inputs	1 x Volt Free Digital Input (std enclosure), 8 x Digital Inputs (medium enclosure)			
Total Available Output Current	Output 3A maximum, available for loop current + sounder outputs + aux supply			
Mains Supply	200-240v 46-63Hz AC (+10% - 15% tolerance) 1.0A max			
Charger Current	1A temperature compensated			
Serial Port	1 x On-Board RS232 connection for PC, modem, IP or portable printer			
USB Interface	1 x USB B type connection for PC communication			
Programming	ming On-Board keypad or PC running Windows tools			
Event Log	5000 event & diagnostics + 500 fire			
Printer (Optional)	On-Board - Medium (M) enclosure only			
Networking	Optional plug in Network Card (HS-503-std or HS-509-fault tolerant)			
Enclosure	Steel IP30 / Radon MW334E Interpon powdercoat			
Cable Entry	Via 20mm knockouts at top and rear of cabinet			
Size, H x W x D mm	Std Enclosure: 340 x 340 x 85 Medium Enclosure (M): 340 x 430 x 115			

Models	Loops	Battery Capacity
HS-5101	1	24v 4Ah internal (min), 24v 7Ah internal (max)
HS-5101M	1	24v 4Ah internal (min), 24v 12Ah internal (max)